
FILTER OVERVIEW WITH SERVICE INTERVALS AND CAPACITIES

6J Series - 1704 and 1904 Tractors

CAB

AIR FILTER - AL225552

Change as required.



ENGINE

PRIMARY FUEL FILTER
RE541922

SECONDARY FUEL FILTER
RE541925

Replace every 250 hours.



ENGINE

PRIMARY AIR FILTER
AL172780

SECONDARY AIR FILTER
AL150288

Replace after every 1500 hours or 2 years (whichever comes first) or after 5 cleanings of the primary element.



ENGINE

OIL FILTER
RE504836

Change after first 100 hours and then every 500 hours.

(Click here for **capacity**)



HYDRAULIC

OIL FILTER - AL169573

Replace after first 100 hours then after 750 hours. Replace after every 2 years or 1500 hours which ever comes first.

(Click here for **capacity**)



TRANSMISSION

OIL FILTER - AL221066

Replace after first 100 hours then after 750 hours. Replace after every 2 years or 1500 hours which ever comes first.

(Click here for **capacity**)



JOHN DEERE
Genuine Parts and Service

http://www.deere.com/en_US/parts/servicessupport/filteroverviews

Mar 2021. Release Date.

CAPACITIES
6J Series - 1704 and 1904 Tractors

CAPACITIES (Approximate):

Fuel Tank:

.....372 L (98.2 gal)

Cooling System:
Cool-Gard™ II

.....28 L (7.4 gal)

Crankcase with Filter:
Plus-50™ II

.....19 L (5 gal)

Transmission and Hydraulic System:
Hy-Gard™

(Including +3 liter for MFWD drop box) .....80 L (21.1 gal)

Mechanical Front Wheel Drive (MFWD) Standard:
Hy-Gard™

.....7.6 L (2 gal)

Mechanical Front Wheel Drive (MFWD) Hubs (Each):
Hy-Gard™

.....1.8 L (0.45 gal)

Return to Filter Overview

JOHN DEERE
Genuine Parts and Service

Mar 2021. Release Date.